

DL9230 User Manual For Relay Function

1) Wire Connection

There are 2 relays for DL9230, 2 wires for each.

Relay 1: Blue and White

Relay 2: Green and Yellow

Connect two wires to turn on the relay, and disconnect to turn off.

2) Command

	Reader address	Data Length	Command	Command Code	End Mark
Turn On R1	0x01	0x05	0x03	0x13	0x03
Turn Off R1	0x01	0x05	0x03	0x12	0x03
Turn On R2	0x01	0x05	0x03	0x23	0x03
Turn Off R2	0x01	0x05	0x03	0x22	0x03
Reader Return	FF	FF	01	13	EE

Note: Please stop reading tag when operating the relay.